

Writing s390 channel device drivers

Cornelia Huck <cornelia.huck@de.ibm.com>

Writing s390 channel device drivers

by Cornelia Huck

Copyright © 2007 IBM Corp.

This documentation is free software; you can redistribute it and/or modify it under the terms of the GNU General Public License as published by the Free Software Foundation; either version 2 of the License, or (at your option) any later version.

This program is distributed in the hope that it will be useful, but WITHOUT ANY WARRANTY; without even the implied warranty of MERCHANTABILITY or FITNESS FOR A PARTICULAR PURPOSE. See the GNU General Public License for more details.

You should have received a copy of the GNU General Public License along with this program; if not, write to the Free Software Foundation, Inc., 59 Temple Place, Suite 330, Boston, MA 02111-1307 USA

For more details see the file COPYING in the source distribution of Linux.

Table of Contents

1. Introduction	1
2. The ccw bus	2
I/O functions for channel-attached devices	2
ccw devices	16
The channel-measurement facility	49
3. The ccwgroup bus	55
ccw group devices	55
4. Generic interfaces	65
register_adapter_interrupt	66
unregister_adapter_interrupt	67
airq_iv_create	68
airq_iv_release	69
airq_iv_alloc	70
airq_iv_free	71
airq_iv_scan	72

Chapter 1. Introduction

This document describes the interfaces available for device drivers that drive s390 based channel attached I/O devices. This includes interfaces for interaction with the hardware and interfaces for interacting with the common driver core. Those interfaces are provided by the s390 common I/O layer.

The document assumes a familiarity with the technical terms associated with the s390 channel I/O architecture. For a description of this architecture, please refer to the "z/Architecture: Principles of Operation", IBM publication no. SA22-7832.

While most I/O devices on a s390 system are typically driven through the channel I/O mechanism described here, there are various other methods (like the diag interface). These are out of the scope of this document.

Some additional information can also be found in the kernel source under `Documentation/s390/driver-model.txt`.

Chapter 2. The ccw bus

The ccw bus typically contains the majority of devices available to a s390 system. Named after the channel command word (ccw), the basic command structure used to address its devices, the ccw bus contains so-called channel attached devices. They are addressed via I/O subchannels, visible on the css bus. A device driver for channel-attached devices, however, will never interact with the subchannel directly, but only via the I/O device on the ccw bus, the ccw device.

I/O functions for channel-attached devices

Some hardware structures have been translated into C structures for use by the common I/O layer and device drivers. For more information on the hardware structures represented here, please consult the Principles of Operation.

Name

struct ccw1 — channel command word

Synopsis

```
struct ccw1 {  
    __u8 cmd_code;  
    __u8 flags;  
    __u16 count;  
    __u32 cda;  
};
```

Members

cmd_code	command code
flags	flags, like IDA addressing, etc.
count	byte count
cda	data address

Description

The ccw is the basic structure to build channel programs that perform operations with the device or the control unit. Only Format-1 channel command words are supported.

Name

struct erw — extended report word

Synopsis

```
struct erw {
    __u32 res0:3;
    __u32 auth:1;
    __u32 pvrf:1;
    __u32 cpt:1;
    __u32 fsavf:1;
    __u32 cons:1;
    __u32 scavf:1;
    __u32 fsaf:1;
    __u32 scnt:6;
    __u32 res16:16;
};
```

Members

res0	reserved
auth	authorization check
pvrf	path-verification-required flag
cpt	channel-path timeout
fsavf	failing storage address validity flag
cons	concurrent sense
scavf	secondary ccw address validity flag
fsaf	failing storage address format
scnt	sense count, if <i>cons</i> == 1
res16	reserved

Name

struct erw_eadm — EADM Subchannel extended report word

Synopsis

```
struct erw_eadm {
    __u32 b:1;
    __u32 r:1;
};
```

Members

b aob error

r arsb error

Name

struct sublog — subchannel logout area

Synopsis

```
struct sublog {
    __u32 res0:1;
    __u32 esf:7;
    __u32 lpum:8;
    __u32 arep:1;
    __u32 fvf:5;
    __u32 sacc:2;
    __u32 termc:2;
    __u32 devsc:1;
    __u32 serr:1;
    __u32 ioerr:1;
    __u32 seqc:3;
};
```

Members

res0	reserved
esf	extended status flags
lpum	last path used mask
arep	ancillary report
fvf	field-validity flags
sacc	storage access code
termc	termination code
devsc	device-status check
serr	secondary error
ioerr	i/o-error alert
seqc	sequence code

Name

struct esw0 — Format 0 Extended Status Word (ESW)

Synopsis

```
struct esw0 {
    struct sublog sublog;
    struct erw erw;
    __u32 faddr[2];
    __u32 saddr;
};
```

Members

sublog	subchannel logout
erw	extended report word
faddr[2]	failing storage address
saddr	secondary ccw address

Name

struct esw1 — Format 1 Extended Status Word (ESW)

Synopsis

```
struct esw1 {  
    __u8 zero0;  
    __u8 lpum;  
    __u16 zero16;  
    struct erw erw;  
    __u32 zeros[3];  
};
```

Members

zero0	reserved zeros
lpum	last path used mask
zero16	reserved zeros
erw	extended report word
zeros[3]	three fullwords of zeros

Name

struct esw2 — Format 2 Extended Status Word (ESW)

Synopsis

```
struct esw2 {
    __u8 zero0;
    __u8 lpum;
    __u16 dcti;
    struct erw erw;
    __u32 zeros[3];
};
```

Members

zero0	reserved zeros
lpum	last path used mask
dcti	device-connect-time interval
erw	extended report word
zeros[3]	three fullwords of zeros

Name

struct esw3 — Format 3 Extended Status Word (ESW)

Synopsis

```
struct esw3 {  
    __u8 zero0;  
    __u8 lpum;  
    __u16 res;  
    struct erw erw;  
    __u32 zeros[3];  
};
```

Members

zero0	reserved zeros
lpum	last path used mask
res	reserved
erw	extended report word
zeros[3]	three fullwords of zeros

Name

struct esw_eadm — EADM Subchannel Extended Status Word (ESW)

Synopsis

```
struct esw_eadm {  
    __u32 sublog;  
    struct erw_eadm erw;  
};
```

Members

sublog	subchannel logout
erw	extended report word

Name

struct irb — interruption response block

Synopsis

```
struct irb {  
    union scsw scsw;  
    union esw;  
    __u8 ecw[32];  
};
```

Members

scsw	subchannel status word
esw	extended status word
ecw[32]	extended control word

Description

The irb that is handed to the device driver when an interrupt occurs. For solicited interrupts, the common I/O layer already performs checks whether a field is valid; a field not being valid is always passed as 0. If a unit check occurred, *ecw* may contain sense data; this is retrieved by the common I/O layer itself if the device doesn't support concurrent sense (so that the device driver never needs to perform basic sense itself). For unsolicited interrupts, the irb is passed as-is (expect for sense data, if applicable).

Name

struct ciw — command information word (CIW) layout

Synopsis

```
struct ciw {  
    __u32 et:2;  
    __u32 reserved:2;  
    __u32 ct:4;  
    __u32 cmd:8;  
    __u32 count:16;  
};
```

Members

et	entry type
reserved	reserved bits
ct	command type
cmd	command code
count	command count

Name

struct ccw_dev_id — unique identifier for ccw devices

Synopsis

```
struct ccw_dev_id {
    u8 ssid;
    u16 devno;
};
```

Members

ssid subchannel set id

devno device number

Description

This structure is not directly based on any hardware structure. The hardware identifies a device by its device number and its subchannel, which is in turn identified by its id. In order to get a unique identifier for ccw devices across subchannel sets, *struct ccw_dev_id* has been introduced.

Name

`ccw_dev_id_is_equal` — compare two `ccw_dev_ids`

Synopsis

```
int ccw_dev_id_is_equal (struct ccw_dev_id * dev_id1, struct ccw_dev_id  
* dev_id2);
```

Arguments

dev_id1 a `ccw_dev_id`

dev_id2 another `ccw_dev_id`

Returns

1 if the two structures are equal field-by-field, 0 if not.

Context

any

Name

`pathmask_to_pos` — find the position of the left-most bit in a pathmask

Synopsis

```
u8 pathmask_to_pos (u8 mask);
```

Arguments

mask pathmask with at least one bit set

ccw devices

Devices that want to initiate channel I/O need to attach to the ccw bus. Interaction with the driver core is done via the common I/O layer, which provides the abstractions of ccw devices and ccw device drivers.

The functions that initiate or terminate channel I/O all act upon a ccw device structure. Device drivers must not bypass those functions or strange side effects may happen.

Name

struct ccw_device — channel attached device

Synopsis

```
struct ccw_device {
    spinlock_t * ccwlock;
    struct ccw_device_id id;
    struct ccw_driver * drv;
    struct device dev;
    int online;
    void (* handler) (struct ccw_device *, unsigned long, struct irb *);
};
```

Members

ccwlock	pointer to device lock
id	id of this device
drv	ccw driver for this device
dev	embedded device structure
online	online status of device
handler	interrupt handler

Description

handler is a member of the device rather than the driver since a driver can have different interrupt handlers for different ccw devices (multi-subchannel drivers).

Name

struct ccw_driver — device driver for channel attached devices

Synopsis

```
struct ccw_driver {
    struct ccw_device_id * ids;
    int (* probe) (struct ccw_device *);
    void (* remove) (struct ccw_device *);
    int (* set_online) (struct ccw_device *);
    int (* set_offline) (struct ccw_device *);
    int (* notify) (struct ccw_device *, int);
    void (* path_event) (struct ccw_device *, int *);
    void (* shutdown) (struct ccw_device *);
    int (* prepare) (struct ccw_device *);
    void (* complete) (struct ccw_device *);
    int (* freeze) (struct ccw_device *);
    int (* thaw) (struct ccw_device *);
    int (* restore) (struct ccw_device *);
    enum uc_todo (* uc_handler) (struct ccw_device *, struct irb *);
    struct device_driver driver;
    enum interruption_class int_class;
};
```

Members

ids	ids supported by this driver
probe	function called on probe
remove	function called on remove
set_online	called when setting device online
set_offline	called when setting device offline
notify	notify driver of device state changes
path_event	notify driver of channel path events
shutdown	called at device shutdown
prepare	prepare for pm state transition
complete	undo work done in <i>prepare</i>
freeze	callback for freezing during hibernation snapshotting
thaw	undo work done in <i>freeze</i>
restore	callback for restoring after hibernation
uc_handler	callback for unit check handler
driver	embedded device driver structure

int_class interruption class to use for accounting interrupts

Name

`ccw_device_set_offline` — disable a ccw device for I/O

Synopsis

```
int ccw_device_set_offline (struct ccw_device * cdev);
```

Arguments

cdev target ccw device

Description

This function calls the driver's `set_offline` function for *cdev*, if given, and then disables *cdev*.

Returns

0 on success and a negative error value on failure.

Context

enabled, ccw device lock not held

Name

`ccw_device_set_online` — enable a ccw device for I/O

Synopsis

```
int ccw_device_set_online (struct ccw_device * cdev);
```

Arguments

cdev target ccw device

Description

This function first enables *cdev* and then calls the driver's `set_online` function for *cdev*, if given. If `set_online` returns an error, *cdev* is disabled again.

Returns

0 on success and a negative error value on failure.

Context

enabled, ccw device lock not held

Name

`get_ccwdev_by_dev_id` — obtain device from a ccw device id

Synopsis

```
struct ccw_device * get_ccwdev_by_dev_id (struct ccw_dev_id * dev_id);
```

Arguments

dev_id id of the device to be searched

Description

This function searches all devices attached to the ccw bus for a device matching *dev_id*.

Returns

If a device is found its reference count is increased and returned; else NULL is returned.

Name

`get_ccwdev_by_busid` — obtain device from a bus id

Synopsis

```
struct ccw_device * get_ccwdev_by_busid (struct ccw_driver * cdrv, const  
char * bus_id);
```

Arguments

cdrv driver the device is owned by

bus_id bus id of the device to be searched

Description

This function searches all devices owned by *cdrv* for a device with a bus id matching *bus_id*.

Returns

If a match is found, its reference count of the found device is increased and it is returned; else NULL is returned.

Name

`ccw_driver_register` — register a ccw driver

Synopsis

```
int ccw_driver_register (struct ccw_driver * cdriver);
```

Arguments

cdriver driver to be registered

Description

This function is mainly a wrapper around `driver_register`.

Returns

0 on success and a negative error value on failure.

Name

`ccw_driver_unregister` — deregister a ccw driver

Synopsis

```
void ccw_driver_unregister (struct ccw_driver * cdriver);
```

Arguments

cdriver driver to be deregistered

Description

This function is mainly a wrapper around `driver_unregister`.

Name

`ccw_device_siosl` — initiate logging

Synopsis

```
int ccw_device_siosl (struct ccw_device * cdev);
```

Arguments

cdev ccw device

Description

This function is used to invoke model-dependent logging within the channel subsystem.

Name

`ccw_device_set_options_mask` — set some options and unset the rest

Synopsis

```
int ccw_device_set_options_mask (struct ccw_device * cdev, unsigned long
flags);
```

Arguments

cdev device for which the options are to be set

flags options to be set

Description

All flags specified in *flags* are set, all flags not specified in *flags* are cleared.

Returns

0 on success, -EINVAL on an invalid flag combination.

Name

`ccw_device_set_options` — set some options

Synopsis

```
int ccw_device_set_options (struct ccw_device * cdev, unsigned long
flags);
```

Arguments

cdev device for which the options are to be set

flags options to be set

Description

All flags specified in *flags* are set, the remainder is left untouched.

Returns

0 on success, -EINVAL if an invalid flag combination would ensue.

Name

`ccw_device_clear_options` — clear some options

Synopsis

```
void ccw_device_clear_options (struct ccw_device * cdev, unsigned long  
flags);
```

Arguments

cdev device for which the options are to be cleared

flags options to be cleared

Description

All flags specified in *flags* are cleared, the remainder is left untouched.

Name

`ccw_device_is_pathgroup` — determine if paths to this device are grouped

Synopsis

```
int ccw_device_is_pathgroup (struct ccw_device * cdev);
```

Arguments

cdev ccw device

Description

Return non-zero if there is a path group, zero otherwise.

Name

`ccw_device_is_multipath` — determine if device is operating in multipath mode

Synopsis

```
int ccw_device_is_multipath (struct ccw_device * cdev);
```

Arguments

cdev ccw device

Description

Return non-zero if device is operating in multipath mode, zero otherwise.

Name

`ccw_device_clear` — terminate I/O request processing

Synopsis

```
int ccw_device_clear (struct ccw_device * cdev, unsigned long intparm);
```

Arguments

cdev target ccw device

intparm interruption parameter; value is only used if no I/O is outstanding, otherwise the *intparm* associated with the I/O request is returned

Description

`ccw_device_clear` calls `csch` on *cdev*'s subchannel.

Returns

0 on success, `-ENODEV` on device not operational, `-EINVAL` on invalid device state.

Context

Interrupts disabled, ccw device lock held

Name

`ccw_device_start_key` — start a s390 channel program with key

Synopsis

```
int ccw_device_start_key (struct ccw_device * cdev, struct ccw1 * cpa,  
unsigned long intparm, __u8 lpm, __u8 key, unsigned long flags);
```

Arguments

<i>cdev</i>	target ccw device
<i>cpa</i>	logical start address of channel program
<i>intparm</i>	user specific interruption parameter; will be presented back to <i>cdev</i> 's interrupt handler. Allows a device driver to associate the interrupt with a particular I/O request.
<i>lpm</i>	defines the channel path to be used for a specific I/O request. A value of 0 will make cio use the opm.
<i>key</i>	storage key to be used for the I/O
<i>flags</i>	additional flags; defines the action to be performed for I/O processing.

Description

Start a S/390 channel program. When the interrupt arrives, the IRQ handler is called, either immediately, delayed (dev-end missing, or sense required) or never (no IRQ handler registered).

Returns

0, if the operation was successful; -EBUSY, if the device is busy, or status pending; -EACCES, if no path specified in *lpm* is operational; -ENODEV, if the device is not operational.

Context

Interrupts disabled, ccw device lock held

Name

`ccw_device_start_timeout_key` — start a s390 channel program with timeout and key

Synopsis

```
int ccw_device_start_timeout_key (struct ccw_device * cdev, struct ccw1
* cpa, unsigned long intparm, __u8 lpm, __u8 key, unsigned long flags,
int expires);
```

Arguments

<i>cdev</i>	target ccw device
<i>cpa</i>	logical start address of channel program
<i>intparm</i>	user specific interruption parameter; will be presented back to <i>cdev</i> 's interrupt handler. Allows a device driver to associate the interrupt with a particular I/O request.
<i>lpm</i>	defines the channel path to be used for a specific I/O request. A value of 0 will make cio use the opm.
<i>key</i>	storage key to be used for the I/O
<i>flags</i>	additional flags; defines the action to be performed for I/O processing.
<i>expires</i>	timeout value in jiffies

Description

Start a S/390 channel program. When the interrupt arrives, the IRQ handler is called, either immediately, delayed (dev-end missing, or sense required) or never (no IRQ handler registered). This function notifies the device driver if the channel program has not completed during the time specified by *expires*. If a timeout occurs, the channel program is terminated via xsch, hsch or csch, and the device's interrupt handler will be called with an irb containing ERR_PTR(-ETIMEDOUT).

Returns

0, if the operation was successful; -EBUSY, if the device is busy, or status pending; -EACCES, if no path specified in *lpm* is operational; -ENODEV, if the device is not operational.

Context

Interrupts disabled, ccw device lock held

Name

`ccw_device_start` — start a s390 channel program

Synopsis

```
int ccw_device_start (struct ccw_device * cdev, struct ccw1 * cpa,  
unsigned long intparm, __u8 lpm, unsigned long flags);
```

Arguments

cdev target ccw device

cpa logical start address of channel program

intparm user specific interruption parameter; will be presented back to *cdev*'s interrupt handler. Allows a device driver to associate the interrupt with a particular I/O request.

lpm defines the channel path to be used for a specific I/O request. A value of 0 will make cio use the opm.

flags additional flags; defines the action to be performed for I/O processing.

Description

Start a S/390 channel program. When the interrupt arrives, the IRQ handler is called, either immediately, delayed (dev-end missing, or sense required) or never (no IRQ handler registered).

Returns

0, if the operation was successful; -EBUSY, if the device is busy, or status pending; -EACCES, if no path specified in *lpm* is operational; -ENODEV, if the device is not operational.

Context

Interrupts disabled, ccw device lock held

Name

`ccw_device_start_timeout` — start a s390 channel program with timeout

Synopsis

```
int ccw_device_start_timeout (struct ccw_device * cdev, struct ccw1 *  
cpa, unsigned long intparm, __u8 lpm, unsigned long flags, int expires);
```

Arguments

<i>cdev</i>	target ccw device
<i>cpa</i>	logical start address of channel program
<i>intparm</i>	user specific interruption parameter; will be presented back to <i>cdev</i> 's interrupt handler. Allows a device driver to associate the interrupt with a particular I/O request.
<i>lpm</i>	defines the channel path to be used for a specific I/O request. A value of 0 will make cio use the opm.
<i>flags</i>	additional flags; defines the action to be performed for I/O processing.
<i>expires</i>	timeout value in jiffies

Description

Start a S/390 channel program. When the interrupt arrives, the IRQ handler is called, either immediately, delayed (dev-end missing, or sense required) or never (no IRQ handler registered). This function notifies the device driver if the channel program has not completed during the time specified by *expires*. If a timeout occurs, the channel program is terminated via xsch, hsch or csch, and the device's interrupt handler will be called with an irb containing ERR_PTR(-ETIMEDOUT).

Returns

0, if the operation was successful; -EBUSY, if the device is busy, or status pending; -EACCES, if no path specified in *lpm* is operational; -ENODEV, if the device is not operational.

Context

Interrupts disabled, ccw device lock held

Name

`ccw_device_halt` — halt I/O request processing

Synopsis

```
int ccw_device_halt (struct ccw_device * cdev, unsigned long intparm);
```

Arguments

cdev target ccw device

intparm interruption parameter; value is only used if no I/O is outstanding, otherwise the `intparm` associated with the I/O request is returned

Description

`ccw_device_halt` calls `hsch` on *cdev*'s subchannel.

Returns

0 on success, `-ENODEV` on device not operational, `-EINVAL` on invalid device state, `-EBUSY` on device busy or interrupt pending.

Context

Interrupts disabled, ccw device lock held

Name

`ccw_device_resume` — resume channel program execution

Synopsis

```
int ccw_device_resume (struct ccw_device * cdev);
```

Arguments

cdev target ccw device

Description

`ccw_device_resume` calls `rsch` on *cdev*'s subchannel.

Returns

0 on success, `-ENODEV` on device not operational, `-EINVAL` on invalid device state, `-EBUSY` on device busy or interrupt pending.

Context

Interrupts disabled, ccw device lock held

Name

`ccw_device_get_ciw` — Search for CIW command in extended sense data.

Synopsis

```
struct ciw * ccw_device_get_ciw (struct ccw_device * cdev, __u32 ct);
```

Arguments

cdev ccw device to inspect

ct command type to look for

Description

During SenseID, command information words (CIWs) describing special commands available to the device may have been stored in the extended sense data. This function searches for CIWs of a specified command type in the extended sense data.

Returns

NULL if no extended sense data has been stored or if no CIW of the specified command type could be found, else a pointer to the CIW of the specified command type.

Name

`ccw_device_get_path_mask` — get currently available paths

Synopsis

```
__u8 ccw_device_get_path_mask (struct ccw_device * cdev);
```

Arguments

cdev ccw device to be queried

Returns

0 if no subchannel for the device is available, else the mask of currently available paths for the ccw device's subchannel.

Name

`ccw_device_get_chp_desc` — return newly allocated channel-path descriptor

Synopsis

```
struct channel_path_desc * ccw_device_get_chp_desc (struct ccw_device  
* cdev, int chp_idx);
```

Arguments

cdev device to obtain the descriptor for

chp_idx index of the channel path

Description

On success return a newly allocated copy of the channel-path description data associated with the given channel path. Return `NULL` on error.

Name

`ccw_device_get_id` — obtain a ccw device id

Synopsis

```
void ccw_device_get_id (struct ccw_device * cdev, struct ccw_dev_id *  
dev_id);
```

Arguments

cdev device to obtain the id for

dev_id where to fill in the values

Name

`ccw_device_tm_start_key` — perform start function

Synopsis

```
int ccw_device_tm_start_key (struct ccw_device * cdev, struct tcw * tcw,
unsigned long intparm, u8 lpm, u8 key);
```

Arguments

<i>cdev</i>	ccw device on which to perform the start function
<i>tcw</i>	transport-command word to be started
<i>intparm</i>	user defined parameter to be passed to the interrupt handler
<i>lpm</i>	mask of paths to use
<i>key</i>	storage key to use for storage access

Description

Start the tcw on the given ccw device. Return zero on success, non-zero otherwise.

Name

`ccw_device_tm_start_timeout_key` — perform start function

Synopsis

```
int ccw_device_tm_start_timeout_key (struct ccw_device * cdev, struct
tcw * tcw, unsigned long intparm, u8 lpm, u8 key, int expires);
```

Arguments

cdev ccw device on which to perform the start function

tcw transport-command word to be started

intparm user defined parameter to be passed to the interrupt handler

lpm mask of paths to use

key storage key to use for storage access

expires time span in jiffies after which to abort request

Description

Start the *tcw* on the given ccw device. Return zero on success, non-zero otherwise.

Name

`ccw_device_tm_start` — perform start function

Synopsis

```
int ccw_device_tm_start (struct ccw_device * cdev, struct tcw * tcw,
unsigned long intparm, u8 lpm);
```

Arguments

cdev ccw device on which to perform the start function

tcw transport-command word to be started

intparm user defined parameter to be passed to the interrupt handler

lpm mask of paths to use

Description

Start the tcw on the given ccw device. Return zero on success, non-zero otherwise.

Name

`ccw_device_tm_start_timeout` — perform start function

Synopsis

```
int ccw_device_tm_start_timeout (struct ccw_device * cdev, struct tcw
* tcw, unsigned long intparm, u8 lpm, int expires);
```

Arguments

cdev ccw device on which to perform the start function

tcw transport-command word to be started

intparm user defined parameter to be passed to the interrupt handler

lpm mask of paths to use

expires time span in jiffies after which to abort request

Description

Start the tcw on the given ccw device. Return zero on success, non-zero otherwise.

Name

`ccw_device_get_mdc` — accumulate max data count

Synopsis

```
int ccw_device_get_mdc (struct ccw_device * cdev, u8 mask);
```

Arguments

cdev ccw device for which the max data count is accumulated

mask mask of paths to use

Description

Return the number of 64K-bytes blocks all paths at least support for a transport command. Return values ≤ 0 indicate failures.

Name

`ccw_device_tm_intrg` — perform interrogate function

Synopsis

```
int ccw_device_tm_intrg (struct ccw_device * cdev);
```

Arguments

cdev ccw device on which to perform the interrogate function

Description

Perform an interrogate function on the given ccw device. Return zero on success, non-zero otherwise.

Name

`ccw_device_get_schid` — obtain a subchannel id

Synopsis

```
void ccw_device_get_schid (struct ccw_device * cdev, struct subchan-  
nel_id * schid);
```

Arguments

cdev device to obtain the id for

schid where to fill in the values

The channel-measurement facility

The channel-measurement facility provides a means to collect measurement data which is made available by the channel subsystem for each channel attached device.

Name

arch/s390/include/asm/cmb.h — Document generation inconsistency

Oops

Warning

The template for this document tried to insert the structured comment from the file `arch/s390/include/asm/cmb.h` at this point, but none was found. This dummy section is inserted to allow generation to continue.

Name

`enable_cmf` — switch on the channel measurement for a specific device

Synopsis

```
int enable_cmf (struct ccw_device * cdev);
```

Arguments

cdev The ccw device to be enabled

Description

Returns 0 for success or a negative error value.

Note

If this is called on a device for which channel measurement is already enabled a reset of the measurement data is triggered.

Context

non-atomic

Name

`disable_cmf` — switch off the channel measurement for a specific device

Synopsis

```
int disable_cmf (struct ccw_device * cdev);
```

Arguments

cdev The ccw device to be disabled

Description

Returns 0 for success or a negative error value.

Context

non-atomic

Name

`cmf_read` — read one value from the current channel measurement block

Synopsis

```
u64 cmf_read (struct ccw_device * cdev, int index);
```

Arguments

cdev the channel to be read

index the index of the value to be read

Description

Returns the value read or 0 if the value cannot be read.

Context

any

Name

`cmf_readall` — read the current channel measurement block

Synopsis

```
int cmf_readall (struct ccw_device * cdev, struct cmbdata * data);
```

Arguments

cdev the channel to be read

data a pointer to a data block that will be filled

Description

Returns 0 on success, a negative error value otherwise.

Context

any

Chapter 3. The ccwgroup bus

The ccwgroup bus only contains artificial devices, created by the user. Many networking devices (e.g. qeth) are in fact composed of several ccw devices (like read, write and data channel for qeth). The ccwgroup bus provides a mechanism to create a meta-device which contains those ccw devices as slave devices and can be associated with the netdevice.

ccw group devices

Name

struct ccwgroup_device — ccw group device

Synopsis

```
struct ccwgroup_device {
    enum state;
    unsigned int count;
    struct device dev;
    struct work_struct ungroup_work;
    struct ccw_device * cdev[0];
};
```

Members

state	online/offline state
count	number of attached slave devices
dev	embedded device structure
ungroup_work	work to be done when a ccwgroup notifier has action type BUS_NOTIFY_UNBIND_DRIVER
cdev[0]	variable number of slave devices, allocated as needed

Name

struct ccwgroup_driver — driver for ccw group devices

Synopsis

```
struct ccwgroup_driver {
    int (* setup) (struct ccwgroup_device *);
    void (* remove) (struct ccwgroup_device *);
    int (* set_online) (struct ccwgroup_device *);
    int (* set_offline) (struct ccwgroup_device *);
    void (* shutdown) (struct ccwgroup_device *);
    int (* prepare) (struct ccwgroup_device *);
    void (* complete) (struct ccwgroup_device *);
    int (* freeze) (struct ccwgroup_device *);
    int (* thaw) (struct ccwgroup_device *);
    int (* restore) (struct ccwgroup_device *);
    struct device_driver driver;
};
```

Members

setup	function called during device creation to setup the device
remove	function called on remove
set_online	function called when device is set online
set_offline	function called when device is set offline
shutdown	function called when device is shut down
prepare	prepare for pm state transition
complete	undo work done in <i>prepare</i>
freeze	callback for freezing during hibernation snapshotting
thaw	undo work done in <i>freeze</i>
restore	callback for restoring after hibernation
driver	embedded driver structure

Name

`ccwgroup_set_online` — enable a ccwgroup device

Synopsis

```
int ccwgroup_set_online (struct ccwgroup_device * gdev);
```

Arguments

gdev target ccwgroup device

Description

This function attempts to put the ccwgroup device into the online state.

Returns

0 on success and a negative error value on failure.

Name

`ccwgroup_set_offline` — disable a ccwgroup device

Synopsis

```
int ccwgroup_set_offline (struct ccwgroup_device * gdev);
```

Arguments

gdev target ccwgroup device

Description

This function attempts to put the ccwgroup device into the offline state.

Returns

0 on success and a negative error value on failure.

Name

`ccwgroup_create_dev` — create and register a ccw group device

Synopsis

```
int ccwgroup_create_dev (struct device * parent, struct ccwgroup_driver  
* gdrv, int num_devices, const char * buf);
```

Arguments

<i>parent</i>	parent device for the new device
<i>gdrv</i>	driver for the new group device
<i>num_devices</i>	number of slave devices
<i>buf</i>	buffer containing comma separated bus ids of slave devices

Description

Create and register a new ccw group device as a child of *parent*. Slave devices are obtained from the list of bus ids given in *buf*.

Returns

0 on success and an error code on failure.

Context

non-atomic

Name

`ccwgroup_driver_register` — register a ccw group driver

Synopsis

```
int ccwgroup_driver_register (struct ccwgroup_driver * cdriver);
```

Arguments

cdriver driver to be registered

Description

This function is mainly a wrapper around `driver_register`.

Name

`ccwgroup_driver_unregister` — deregister a ccw group driver

Synopsis

```
void ccwgroup_driver_unregister (struct ccwgroup_driver * cdriver);
```

Arguments

cdriver driver to be deregistered

Description

This function is mainly a wrapper around `driver_unregister`.

Name

`ccwgroup_probe_ccwdev` — probe function for slave devices

Synopsis

```
int ccwgroup_probe_ccwdev (struct ccw_device * cdev);
```

Arguments

cdev ccw device to be probed

Description

This is a dummy probe function for ccw devices that are slave devices in a ccw group device.

Returns

always 0

Name

`ccwgroup_remove_ccwdev` — remove function for slave devices

Synopsis

```
void ccwgroup_remove_ccwdev (struct ccw_device * cdev);
```

Arguments

cdev ccw device to be removed

Description

This is a remove function for ccw devices that are slave devices in a ccw group device. It sets the ccw device offline and also deregisters the embedding ccw group device.

Chapter 4. Generic interfaces

Some interfaces are available to other drivers that do not necessarily have anything to do with the busses described above, but still are indirectly using basic infrastructure in the common I/O layer. One example is the support for adapter interrupts.

Name

`register_adapter_interrupt` — register adapter interrupt handler

Synopsis

```
int register_adapter_interrupt (struct airq_struct * airq);
```

Arguments

airq pointer to adapter interrupt descriptor

Description

Returns 0 on success, or -EINVAL.

Name

`unregister_adapter_interrupt` — unregister adapter interrupt handler

Synopsis

```
void unregister_adapter_interrupt (struct irq_struct * irq);
```

Arguments

irq pointer to adapter interrupt descriptor

Name

`airq_iv_create` — create an interrupt vector

Synopsis

```
struct airq_iv * airq_iv_create (unsigned long bits, unsigned long  
flags);
```

Arguments

bits number of bits in the interrupt vector

flags allocation flags

Description

Returns a pointer to an interrupt vector structure

Name

`airq_iv_release` — release an interrupt vector

Synopsis

```
void airq_iv_release (struct airq_iv * iv);
```

Arguments

iv pointer to interrupt vector structure

Name

`airq_iv_alloc` — allocate irq bits from an interrupt vector

Synopsis

```
unsigned long airq_iv_alloc (struct airq_iv * iv, unsigned long num);
```

Arguments

iv pointer to an interrupt vector structure

num number of consecutive irq bits to allocate

Description

Returns the bit number of the first irq in the allocated block of irqs, or -1UL if no bit is available or the AIRQ_IV_ALLOC flag has not been specified

Name

`airq_iv_free` — free irq bits of an interrupt vector

Synopsis

```
void airq_iv_free (struct airq_iv * iv, unsigned long bit, unsigned  
long num);
```

Arguments

iv pointer to interrupt vector structure

bit number of the first irq bit to free

num number of consecutive irq bits to free

Name

`airq_iv_scan` — scan interrupt vector for non-zero bits

Synopsis

```
unsigned long airq_iv_scan (struct airq_iv * iv, unsigned long start,  
unsigned long end);
```

Arguments

iv pointer to interrupt vector structure

start bit number to start the search

end bit number to end the search

Description

Returns the bit number of the next non-zero interrupt bit, or -1UL if the scan completed without finding any more any non-zero bits.